

# LR1-F



LR1-F105

F - Range Overload Relays (Independent Mounting)								
	(A)	3- . 50Hz, ..AC3						
		220V	380V	415V	440V	660V	aM (A)	g1 (A)
		KW	KW	KW	KW	KW		
LR1-F105	65 to 105	25	51	55	59	90	105	160
LR1-F125	80 to 125	30	59	59	63	110	125	200
LR1-F160	100 to 160	45	80	80	90	140	160	250
LR1-F200	125 to 200	55	90	100	110	160	200	315
LR1-F250	160 to 250	63	110	129	140	200	250	400
LR1-F315	200 to 315	80	150	160	160	257	315	500
LR1-F400	250 to 400	110	185	200	220	335	400	630
LR1-F500	315 to 500	140	250	257	280	445	500	800
LR1-F630	400 to 630	180	315	355	375	500	630	800
LR1-F800	500 to 800	220	400	425	450	—	-	1000
LR1-F1000	630 to 1000	295	500	500	500	—	-	1250